

## INSTALLATION INSTRUCTIONS FOR THE 201 SERIES FIXTURE

APPLICATION: General/Perimeter Lighting



### STOP! - READ THIS FIRST! - IMPORTANT SAFETY INSTRUCTIONS!

- For information on how to recycle LED/Fluorescent electronic products, please visit [www.epa.gov](http://www.epa.gov).
- Do not install damaged product. This fixture is properly packed to prevent damage during transit.
- All wiring connections should be capped with UL approved recognized wire connectors.
- Do not touch LED diodes or any connecting clips; these parts are very sensitive.
- Do not exceed maximum wattage marked on fixture label.

|                                                                                                                                                                                            |                                                                                                                                                                                                          |
|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Carefully read the instructions pertaining to your fixture thoroughly. <b>IF YOU HAVE ANY QUESTIONS REGARDING THE PROPER INSTALLATION OR LOCAL CODES, CONSULT A QUALIFIED ELECTRICIAN.</b> | Injury to persons and damage to the fixture and/or mounting surface may occur if the fixture is pulled from the surface. To reduce risk of injury or damage, mount only to a mechanically sound surface. |
| Both cord set and hard wired fixtures are intended for connection to a grounded, three-wire source of supply.                                                                              | Install and wire the fixture in locations in accordance with all national, state and local codes.                                                                                                        |
| Do not install outdoors or in applications other than intended use.                                                                                                                        | To avoid shock hazard, do not work with live electrical wires.                                                                                                                                           |
| Ensure fixture is properly grounded before testing.                                                                                                                                        | This fixture is intended for damp/dry applications.                                                                                                                                                      |



**WARNING:** THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTIONS AND OPERATIONS OF THE PRODUCT AND THE HAZARDS INVOLVED.



**WARNING:** RISK OF FIRE; MINIMUM OF 90°C SUPPLY CONDUCTOR SHOULD BE USED. CONSULT A QUALIFIED ELECTRICIAN TO ENSURE CORRECT BRANCH CIRCUIT CONDUCTOR.



**WARNING:** TO AVOID ELECTRIC SHOCK HAZARD, DISCONNECT THE POWER AT THE PANEL BOARD (CIRCUIT BREAKER BOX) BEFORE BEGINNING INSTALLATION.




**WARNING:** TO AVOID FIRE HAZARD RISK, WHEN INSTALLING HARD WIRED UNITS, BE AWARE IF SUPPLY WIRES ARE LOCATED WITHIN THREE INCHES OF BALLAST. IF SO, USE WIRE RATED FOR AT LEAST 90°C (194°F). IF UNSURE, CONSULT A QUALIFIED ELECTRICIAN BEFORE INSTALLING.

**1**




**REMINDER:** TO AVOID ELECTRIC SHOCK HAZARD, DISCONNECT THE POWER AT THE PANEL BOARD (CIRCUIT BOX) BEFORE BEGINNING INSTALLATION!

**2**




Carefully remove fixture from packaging. Use gloves to prevent dirt and oils from transferring to the unit. Inspect the fixture for any defects before proceeding.

**3**




**CAUTION: EDGES MAY BE SHARP:** Carefully remove lens from fixture by gently un-snapping one side at a time, and set aside.

**4**




Remove LED assembly by squeezing in on the sides of the tray until the tabs clear the slot, and pull upwards. Set the assembly aside.

**5**




Remove 7/8" knockout from bottom of fixture in desired location. Bring the supply wiring thru the knockout.

**6**




Surface mount the fixture to a secure location by installing appropriate hardware to the locations shown above.

**7**




Connect the wiring to the incoming supply using the quick clip (if provided). **Always follow all local, state, and national codes!** Test the fixture.

**8**



Reinstall the LED assembly by squeezing in on the tabs, and gently push the assembly in to the tray until it snaps in.

**9**



Reinstall the lens to the fixture by gently pressing down on the lens until it snaps in to place.